

DRIFTSTIDER OCH LADDTIDER



	Motorsåg			Stamkvistare		Trimmer				Kombimaskin	Häcksax			Stånghäcksax	
Batteri	MSA 160 T	MSA 160 C-BQ	MSA 200 C-BQ	HTA 65	HTA 85	FSA 65	FSA 85	FSA 90 ^③	FSA 130 ^③	KMA 130 R ^③	HSA 66	HSA 86	HSA 94 R/94 T	HLA 65	HLA 85
AP 100	15	15	15	15	15	25	15	10	16/12/8 ^①	13/8/6 ^①	60	60	45/40/35 ^①	60	60
AP 200	35	35	35	35	35	50	30	20	25/20/15 ^①	26/15/13 ^①	120	120	90/80/70 ^①	120	120
AP 300	50	50	45	55	55	75	45	30	40/30/20 ^①	38/23/18 ^①	180	180	135/120/105 ^①	180	180
AR 1000	125	125	110	125	125	200	120	80	100/85/70 ^①	100/63/50 ^①	450	450	380/350/320 ^①	450	450
AR 2000	180	180	160	180	180	300	180	120	150/120/100 ^①	150/90/75 ^①	660	660	550/500/450 ^①	660	660
AR 3000	230	230	200	230	230	380	220	150	190/150/125 ^①	190/115/90	800	800	700/630/570 ^①	800	800



	Lövlås		Sopmaskin	Kapmaskin	Sekatör		Gräsklippare (m ²)			Laddare (80/100%)			
Batteri	BGA 85	BGA 100	KGA 770	TSA 230	ASA 65	ASA 85	RMA 443 C/TC	RMA 448 TC	RMA 2 RT	Batteri	AL 101	AL 300	AL 500
AP 100	8	27/11/7/7 ^②	70	6	210	200	200	150	200	AP 100	60/90	25/50	25/35
AP 200	16	55/22/13/10 ^②	140	12	420	400	350	300	350	AP 200	125/165	30/55	25/35
AP 300	24	83/33/21/16 ^②	210	18	630	600	500	450	500	AP 300	190/250	45/75	25/35
AR 1000	65	225/95/60/45 ^②	—	50	—	—	—	—	—	AR 1000	—	130/180	90/120
AR 2000	90	300/130/80/60 ^②	—	75	—	—	—	—	—	AR 2000	—	190/250	100/130
AR 3000	115	395/160/100/75 ^②	—	95	—	—	—	—	—	AR 3000	—	220/300	120/160

■ Rekommenderat batteri
 ■ Maskinen i reducerat effektläge
 ^① Steg 1/Steg 2/Steg 3
 ^② Steg 1/Steg 2/Steg 3/Boost
 ^③ Med trimmerhuvud
 Samtliga drifts- och laddtider är angivna i minuter, undantaget gräsklippare där driftstiden är angiven i m².