







# DRIFTSTIDER OCH LADDTIDER

Lithium-Ion  
PRO

STIHL



	MOTORSÅG			STAMKVISTARE		TRIMMER				KOMBI-MASKIN	HÄCKSAX			STÅNGHÄCKSAX	
BATTERI	MSA 161 T	MSA 160 C-B	MSA 200 C-B	HTA 65	HTA 85	FSA 65	FSA 85	FSA 90 <sup>①</sup>	FSA 130 <sup>①</sup>	KMA 130 R <sup>①</sup>	HSA 66	HSA 86	HSA 94 R/94 T	HLA 65	HLA 85
<b>AP 100</b>	-	-	-	18	18	30	18	12	19-10 <sup>①</sup>	16-7 <sup>①</sup>	72	72	54-42 <sup>①</sup>	72	72
<b>AP 200</b>	42	42	42	42	42	60	36	24	30-18 <sup>①</sup>	30-14 <sup>①</sup>	144	144	108-84 <sup>①</sup>	144	144
<b>AP 300</b>	50	50	45	55	55	75	45	30	40-20 <sup>①</sup>	38-18 <sup>①</sup>	180	180	135-105 <sup>①</sup>	180	180
<b>AP 300 S</b>	62	62	56	68	68	93	56	37	50-25 <sup>①</sup>	47-22 <sup>①</sup>	223	223	167-130 <sup>①</sup>	223	223
<b>AR 1000</b>	125	125	110	125	125	200	120	80	100-70 <sup>①</sup>	105-50 <sup>①</sup>	450	450	380-320 <sup>①</sup>	450	450
<b>AR 2000</b>	180	180	160	180	180	300	180	120	150-100 <sup>①</sup>	154-73 <sup>①</sup>	660	660	550-450 <sup>①</sup>	660	660
<b>AR 3000</b>	230	230	200	230	230	380	220	150	190-125 <sup>①</sup>	193-92 <sup>①</sup>	800	800	700-570 <sup>①</sup>	800	800
															
	LÖVBLÅS		SOPMASKIN	KAPMASKIN	GRÄSKLIPPARE (m <sup>2</sup> )			LADDARE (80/100%)							
BATTERI	BGA 85	BGA 100	KGA 770	TSA 230	RMA 443 C/PC	RMA 448 PC	RMA 2 RP	<b>BATTERI</b>			AL 101	AL 300	AL 500		
<b>AP 100</b>	10	32-8 <sup>①</sup>	84	7	240 <sup>②</sup>	180 <sup>②</sup>	240 <sup>②</sup>	<b>AP 100</b>			75/100	30/45	30/45		
<b>AP 200</b>	19	66-12 <sup>①</sup>	168	14	420 <sup>②</sup>	360 <sup>②</sup>	420 <sup>②</sup>	<b>AP 200</b>			150/200	40/55	30/45		
<b>AP 300</b>	24	83-16 <sup>①</sup>	210	18	500 <sup>②</sup>	450 <sup>②</sup>	500 <sup>②</sup>	<b>AP 300</b>			190/250	45/60	25/35		
<b>AP 300 S</b>	30	103-20 <sup>①</sup>	260	22	620 <sup>②</sup>	560 <sup>②</sup>	620 <sup>②</sup>	<b>AP 300 S</b>			230/300	55/70	30/45		
<b>AR 1000</b>	65	225-45 <sup>①</sup>	-	50	-	-	-	<b>AR 1000</b>			-	130/160	90/120		
<b>AR 2000</b>	90	300-60 <sup>①</sup>	-	75	-	-	-	<b>AR 2000</b>			-	190/215	100/130		
<b>AR 3000</b>	115	395-75 <sup>①</sup>	-	95	-	-	-	<b>AR 3000</b>			-	220/265	120/160		

Rekommenderat batteri

Maskinen i reducerat effektläge

① Steg 1 - 3/4

② På PC-modeller med dubbla aktiva batterifack, dubblas klippytan med 2 batterier

③ Med trimmerhuvud

Samtliga drifts- och laddtider är angivna i minuter, undantaget gräsklippare där driftstiden är angiven i m<sup>2</sup>.